



**PARMA:** 12V In-Ground Well Light

**CL-WL5-III**



CLAROLUX® Parma, CL-WL5-III, with optional frosted lens shown above.



CLAROLUX® landscape lighting fixtures are available with LED lamps.



**NOTEABLE FEATURES:**

- ❑ SCREW ON FACEPLATE FOR EASY SERVICING
- ❑ BERYLLIUM COPPER SOCKET WITH SS MR-16 CLIP
- ❑ WATER TIGHT DESIGN
- ❑ SOLID WEATHERED BRASS FACEPLATE
- ❑ HOUSING MANUFACTURED FROM ABS WITH IZOD
- ❑ 10 YEAR WARRANTY

**NOTEABLE FEATURES CONTINUED:**

- ❑ FLUSH GLASS LENS TO PREVENT DEBRIS BUILD-UP
- ❑ ASSEMBLED IN GREENSBORO, NC, USA

**OPTIONAL ACCESSORIES:**

- ❑ OPTIONAL LENSES & LOUVERS (See website for details)
- ❑ WIDE RANGE OF MR16 LAMPS & LEDs

**SPECIFICATIONS:**

**Our Commitment**

At ClaroLux®, our goal is to set the standard in the landscape lighting industry. We are happy to be the exception, not the rule. Every day we challenge ourselves to create new and innovative products that can help revolutionize the low voltage lighting industry. We pride ourselves on being innovative, passionate, and dedicated to setting the standard. What you will find when you purchase from ClaroLux Landscape Lighting® is that the norm is never good enough. We believe in our mission, we believe in ourselves, and we believe in our products. This is why our products come with a structural lifetime warranty.

**Body**

Solid Brass faceplate with casted body. The body of the luminaire is encased by an impact resistant, black, ABS housing. The solid brass faceplate and ABS housing helps to protect the luminaire's body from the elements.

**Lens Cover Gasket**

High temperature silicone for water-tight seal.

**Housing**

The Parma comes with an ABS housing. The housing is rated for high temperatures and is manufactured from impact resistant ABS composite.

**Lens**

Comes with a factory sealed shock resistant tempered glass lens to prevent water and debris intrusion. Glass lens sits flush with top to prevent debris/water buildup. A complete set of designer lenses are available including: frosted, prismatic and many other options (see website for details).

**Lamp**

For use with a halogen lamp up to 35W MR16 lamp. Brilliance LED MR16 lamps are available in 4W, 5W or 7W.

**Electrical Requirements**

A remote 12V transformer required, may be ordered separately from ClaroLux®. Recommended voltage range for 12V halogen lamps is 10.8V - 12V. Recommended voltage range for 12V Brilliance LEDs is 10V - 14V (12V is ideal).

**Lamp Connection**

Spring loaded, pre-greased beryllium copper socket with stainless steel MR16 lamp holder. GU5.3 base.

**Recommended Installation**

ClaroLux® recommends using sand and pea gravel to secure the luminaire in the ground and allow for proper drainage around the luminaire. See Installation Instructions.

**Wiring**

25ft of 18AWG UL Listed, copper wire that is protected by Black Polyvinyl Chloride (PVC). ClaroLux® recommends using copper crimp, lithium filled, grease tube connectors at each connection point (HUB).

**Finish**

ClaroLux's® Parma's in-ground well lights are all assembled in the USA and available with a wide range of lenses and louvers. The Parma's solid brass covers have a "living finish" and can naturally change over time.

**Warranty**

ClaroLux's® 10 Warranty (please see warranty for more details).

**Manufacturing**

Proudly assembled at ClaroLux's® manufacturing facility in Greensboro, NC, USA.