



ROMA: 12V Solid Brass Specialty Light

CL-DL3-III



CLAROLUX[®] landscape lighting fixtures are available with LED lamps.



NOTEABLE FEATURES:

- ❑ INCLUDES MOUNTING HARDWARE
- ❑ BERYLLIUM COPPER SOCKET
- ❑ PRE-GREASED SOCKET
- ❑ WIRE LEAD - 25 FEET 18AWG SPT-2
- ❑ SOLID CAST BRASS CONSTRUCTION
- ❑ SURFACE MOUNTING PLATE FOR EASY INSTALLATION
- ❑ LIFETIME WARRANTY

OPTIONAL ACCESSORIES:

- ❑ DADOED WOOD SLATS (CL-DW48 - See website for details)
- ❑ WIDE RANGE OF BI-PIN LAMPS & LEDs

SPECIFICATIONS:

Our Commitment

At ClaroLux[®], our goal is to set the standard in the landscape lighting industry. We are happy to be the exception, not the rule. Every day we challenge ourselves to create new and innovative products that can help revolutionize the low voltage lighting industry. We pride ourselves on being innovative, passionate, and dedicated to setting the standard. What you will find when you purchase from ClaroLux Landscape Lighting[®] is that the norm is never good enough. We believe in our mission, we believe in ourselves, and we believe in our products. This is why our products come with a structural lifetime warranty.

Body

Manufactured from cast brass.

Lens

Frosted tempered glass lens.

Shroud

Machined set screws on each side of the luminaire for easy relamping and adjusting.

Lamp

For use with a halogen lamp up to 20W T3 bi-pin lamp. Brilliance LED bi-pin lamps are available (1.2W Micro LED bi-pin recommended).

Electrical Requirements

A remote 12V transformer required, may be ordered separately from ClaroLux[®]. Recommended voltage range for 12V halogen lamps is 10.8V - 12V. Recommended voltage range for Brilliance 12V LEDs is 10V - 14V (12V is ideal).

Lamp Connection

Specification grade, beryllium copper lamp holder. GU5.3 base.

Mounting Hardware

Mounting hardware, screws and anchors.

Dadoed Wood Slats

Ideal when mounting luminaires on wood surfaces. The treated 48" wood slats have pre-drilled, mounting holes for finishing nails (not included). The wood slats are designed to easily cover the lead wire of luminaire. The dadoed wood slats are manufactured by ClaroLux in the USA. For more details please visit www.ClaroLux.com.

Wiring

25ft of 18AWG UL Listed, copper wire that is protected by Black Polyvinyl Chloride (PVC). ClaroLux[®] recommends using copper crimp, lithium filled, grease tube connectors at each connection point in the field (HUB).

Finish

ClaroLux's[®] Weathered Brass finish was created especially for ClaroLux's brass luminaire line. The Roma has a "living finish" and will naturally patina and change over time.

Warranty

ClaroLux's[®] Structural Lifetime Warranty (please see warranty for more details).

Manufacturing

Proudly designed at ClaroLux's[®] manufacturing facility in Greensboro, NC, USA.