



**TURIN:** 12V Solid Brass Specialty Light

**CL-DL4-III**



CLAROLUX<sup>®</sup> landscape lighting fixtures are available with LED lamps.



**NOTEABLE FEATURES:**

- ❑ INCLUDES MOUNTING HARDWARE
- ❑ BERYLLIUM COPPER SOCKET
- ❑ PRE-GREASED SOCKET
- ❑ WIRE LEAD - 25 FEET 18AWG SPT-2
- ❑ SOLID STAINLESS STEEL & BRASS CONSTRUCTION
- ❑ SURFACE MOUNTING PLATE FOR EASY INSTALLATION
- ❑ LIFETIME WARRANTY

**OPTIONAL ACCESSORIES:**

- ❑ DADOED WOOD SLATS (CL-DW48 - See website for details)
- ❑ WIDE RANGE OF BI-PIN LAMPS & LEDs

**SPECIFICATIONS:**

**Our Commitment**

At ClaroLux<sup>®</sup>, our goal is to set the standard in the landscape lighting industry. We are happy to be the exception, not the rule. Every day we challenge ourselves to create new and innovative products that can help revolutionize the low voltage lighting industry. We pride ourselves on being innovative, passionate, and dedicated to setting the standard. What you will find when you purchase from ClaroLux Landscape Lighting<sup>®</sup> is that the norm is never good enough. We believe in our mission, we believe in ourselves, and we believe in our products. This is why our products come with a structural lifetime warranty.

**Body**

Manufactured from stainless steel and brass.

**Lens**

Frosted tempered glass lens.

**Shroud**

Brass cover plate with machined set screws on each side of the luminaire for easy relamping and servicing.

**Lamp**

For use with a halogen lamp up to 20W T3 bi-pin lamp. Brilliance LED bi-pin lamps are available (1.2W Micro LED bi-pin recommended).

**Electrical Requirements**

A remote 12V transformer required, may be ordered separately from ClaroLux<sup>®</sup>. Recommended voltage range for 12V halogen lamps is 10.8V - 12V. Recommended voltage range for Brilliance 12V LEDs is 10V - 14V (12V is ideal).

**Lamp Connection**

Specification grade, beryllium copper lamp holder. GU5.3 base.

**Mounting Hardware**

Mounting hardware, screws, weather strip and anchors.

**Dadoed Wood Slats**

Ideal when mounting luminaires on wood surfaces. The treated 48" wood slats have pre-drilled, mounting holes for finishing nails (not included). The wood slats are designed to easily cover the lead wire of luminaire. The dadoed wood slats are manufactured by ClaroLux in the USA. For more details please visit [www.ClaroLux.com](http://www.ClaroLux.com).

**Wiring**

25ft of 18AWG UL Listed, copper wire that is protected by Black Polyvinyl Chloride (PVC). ClaroLux<sup>®</sup> recommends using copper crimp, lithium filled, grease tube connectors at each connection point in the field (HUB).

**Finish**

ClaroLux's<sup>®</sup> Weathered Brass finish was created especially for ClaroLux's brass luminaire line. The Turin has a "living finish" and will naturally patina and change over time.

**Warranty**

ClaroLux's<sup>®</sup> Structural Lifetime Warranty (please see warranty for more details).

**Manufacturing**

Proudly designed at ClaroLux's<sup>®</sup> manufacturing facility in Greensboro, NC, USA.