



LAWNDALE: 12V Solid Brass Up Light

CL-FL36-III



CLAROLUX[®] landscape lighting fixtures are available with LED lamps.



NOTEABLE FEATURES:

- ❑ ROTATABLE SHROUD TO PREVENT LIGHT GLARE
- ❑ MACHINE THREADED BRASS THUMB SCREWS
- ❑ PAR36 ANTI-SLIP TERMINAL FORK CONNECTORS
- ❑ EASY SLIDE ON SHROUD/TOP
- ❑ MANUFACTURED FROM SOLID CAST BRASS
- ❑ LIFETIME WARRANTY
- ❑ ASSEMBLED IN GREENSBORO, NC, USA

OPTIONAL ACCESSORIES:

- ❑ WEATHERED BRASS SURFACE MOUNT (CL-TM23-III)
- ❑ WEATHERED BRASS RISERS (BLEP-III: 6", 12", 24", 36")
- ❑ WEATHERED BRASS COUPLER (CL-COUP-III)
- ❑ WEATHERED BRASS 90 DEGREE FITTING (CL-90DE-III)
- ❑ WIDE RANGE OF HALOGEN PAR36 LAMPS & LEDs

SPECIFICATIONS:

Our Commitment

At ClaroLux[®], our goal is to set the standard in the landscape lighting industry. We are happy to be the exception, not the rule. Every day we challenge ourselves to create new and innovative products that can help revolutionize the low voltage lighting industry. We pride ourselves on being innovative, passionate, and dedicated to setting the standard. What you will find when you purchase from ClaroLux Landscape Lighting[®] is that the norm is never good enough. We believe in our mission, we believe in ourselves, and we believe in our products. This is why our products come with a structural lifetime warranty.

Body

Precision machined from solid cast brass. Body design provides enclosed luminaire and silicone filed wireway to protect luminaire from ants and wicking. Features an integral knuckle for maximum mechanical strength.

Knuckle

Machined brass knuckle with a solid brass adjustable thumbscrew. Vertical tilt of -30° to +210° for precise final adjustment. Thread on the knuckle is 1/2 NPS which easily threads into ClaroLux's[®] patented ground stake and fixture accessories.

Shroud

Precision machined cast brass and comes with two brass thumb screws for field adjustments. Accepts all PAR36 halogen lamps and LEDs. Shroud is rotatable 360° to prevent glare.

Lamp

For use with a PAR36 halogen lamp up to 50W. When using halogen lamps ClaroLux[®] recommends GE PAR36 lamps. Brilliance LED PAR36 lamps are available in 6W, 9W or 12W. Please see LED in the product section of the website for more details).

Electrical Requirements

A remote 12V transformer required, may be ordered separately from ClaroLux[®]. Recommended voltage range for 12V halogen lamps is 10.8V - 12V. Recommended voltage range for 12V Brilliance LEDs is 10V - 22V (12V is ideal).

Lamp Connection

PAR36 screw terminal with heat shrink to protect connection to cable.

Mounting Stake

Standard mounting stake is injection molded ABS with a 1/2" NPS threaded female fitting. Comes with wire slot so luminaire can easily be removed and serviced. The stake color is dark brown to help blend in with the landscape environment.

Wiring

25ft of 16AWG UL Listed, copper wire that is protected by Black Polyvinyl Chloride (PVC). ClaroLux[®] recommends using copper crimp, lithium filled, grease tube connectors at each connection point in the field (HUB).

Finish

ClaroLux's[®] Weathered Brass finish was created especially for ClaroLux's brass luminaire line. The Lawndale has a "living finish" and will naturally patina and change over time.

Warranty

ClaroLux's[®] Structural Lifetime Warranty (please see warranty for more details).

Manufacturing

Proudly designed, finished and assembled at ClaroLux's[®] manufacturing facility in Greensboro, NC, USA.